

L300 10-10

10 + 10 bay charger for HDI 830 and BA 300 |
Assistive Listening, Conference

Cat. No. 502710

General Description

The L 300 10-10 charger quickly charges up to 10 receivers and up to 10 BA 300 rechargeable batteries in parallel. It is especially easy to use since the receivers can be inserted into the charging compartments either way round. Compatible are RI 830/RI 830 S, HDI 830, RI 900, RR 840/RR 840 S receivers and BA 300 rechargeable batteries.



Technical Data

L 300 10-10 charger:

Charging time..... approx. 3 hrs
 Charging current per charging compartment..... approx. 70 mA
 Current consumption max. 2 A
 Voltage..... 6 V
 Weight approx. 530 g
 Dimensions 400 x 130 x 50 mm
 Ambient temperature..... 0 – 40° C

NT 6 mains unit:

Nominal input voltage..... 100 to 240 V~
 Nominal input current max. 0.5 A
 Mains frequency 50 – 60 Hz
 Nominal output voltage 6 V
 Nominal output current..... max. 2.5 A
 Operating temperature range..... 0° C to +45° C
 Storage temperature range..... -25° C to +75° C
 Weight 145 g
 Dimensions 71.7 x 50 x 33.2 mm

Features

- 10 plus 10 bay parallel charging unit for HDI 830 receivers and BA 300 batteries
- LED charging controls
- Full charge in 3 hours
- Mains supply with 4 country adaptors
- Delivery includes: 1 L 300 10-10 charger
 1 NT 6 mains unit with 4 country adapters (EU/UK/US/AU)
 1 instruction manual

Architect & Engineering specs

A mains driven charger shall supply 10 charging compartments for rechargeable batteries plus 10 charging compartments for stetho or bodypack receivers. Both types can be charged at the same time. Mounting plates are available for fixed installation on an even surface. A mains unit with country adaptors for EU, UK, US and AU is included in delivery. The charger shall work with Sennheiser BA 300 batteries as well as RI 830/RI 830 S, HDI 830, RI 900, RR 840/RR 840 S receivers.

Recommended Accessories

- 2 mounting plates Cat. No. 534417
- NT 6 mains unit with 4 country adapters Cat. No. 534404 (EU/UK/US/AU)

